



## TW5340 Multi-Constellation GNSS Smart Antenna

The TW5340 is a multi-constellation GNSS Smart Antenna which provides simultaneous GPS/GLONASS/SBAS reception. It is designed for use in professional grade applications such as precision timing, network synchronization, low current applications, and tracking/positioning applications.

The TW5340 GNSS Smart Antenna uses the state of the art ST STA8088 receiver which provides 32 high sensitivity tracking channels plus 2 fast acquisition channels which can be assigned to acquire and track GPS, GLONASS, QZSS, and SBAS (WAAS, EGNOS, MSAS) signals simultaneously.

The TW5340 employs Tallysman's *Accutenna*™ dual feed antenna patch technology which greatly improves rejection of multi-path signal interference, across the whole GNSS band, making the TW5340 the most precise smart antenna in its size across all operating environments.

The TW5340 accelerates GPS positioning by predicting satellite ephemeris data based on previous observations, resulting in extremely fast Time-To-First-Fix.

The TW5340 can be configured to outputs up to three NMEA 0183 messages lists with navigation update rates up to 10Hz. RS232, and CMOS interfaces are available with input voltage options of 3,3V, 5.0V and 12V ( 12V to 36V option available).

A standard one pulse-per-second 1PPS synchronized to UTC time is available as a single ended output or as a differential output at RS422 levels. NMEA data can also be configured to output at RS422 levels, however the 1PPS output is disabled in this mode.

Tallysman's Windows™ based Configurator enables simple configuration of parameters such as baud rates, output message rates, constellation, tracking parameters, 1PPS configuration and Standby mode parameters.

A non-magnetic version is available with Part Number TW5341



### Features

- Multi-Constellation Receiver/Antenna
- 32 Channel simultaneous operation
- High performance tracking (-162 dBm)
- WAAS, EGNOS, & MSAS enabled
- 3 NMEA 0183 output Lists
- Navigation rates 1 to 10 Hz
- 1 PPS & NMEA configurable RS422 outputs
- Low Current Standby Mode
- *Accutenna*™ Technology
- Excellent multi-path signal rejection
- Industrial grade IP67 enclosure
- RoHS and REACH Compliant



# TW5340 Multi-Constellation GNSS Receiver/Antenna

## Mechanical:

The TW5340/TW5341 is housed in an industrial grade weatherproof IP67 enclosure for 19mm diameter (¾”) thru-hole mount or mast mount installations. It is available with low profile radome or with a conical radome. L-brackets and pipe mount brackets are available as installation options.

## Specifications

<b>Frequencies</b>	GPS / GLONASS / QZSS	<b>1 PPS Output</b>	Single ended & Differential RS422. +/-50 ns Accuracy 16Kv protection RS422 lines
<b>SBAS</b>	WAAS, EGNOS, MSAS	<b>Channels</b>	32 simultaneous plus 2 fast acquisition
<b>Antenna / Axial Ratio</b>	Dual Feed / < 1 dB typical.	<b>Sensitivity</b>	Acquisition: -146 dBm Tracking: -162 dBm
<b>Cable Length</b>	5m (15m & 25m special order)	<b>Time to First Fix</b>	Cold start: 35 sec
<b>Output</b>	RS232, CMOS		Warm start: 30 sec
<b>Voltages</b>	3.3V, 5V, and 12 V 12 V to 36V VDC Option	<b>Serial Protocol</b>	Hot start: <2 sec Reacquisition: <1 sec
<b>Current</b>	120 mA during acquisition 80 mA operating Standby mode < 1mA		Output: NMEA 0183 Baud Rate: 300 to 921,600 bps, 115200 (default) Update Rate: configurable up to 10Hz NMEA Message Configurable
<b>Dimensions</b>	66.5 mm (dia) x 21 mm (h)	<b>Wires</b>	Power, Gnd, Rx Tx, 1 PPS Qualification, Differential 1 PPS-A, Differential 1 PPS-B
<b>Weight</b>	135 g		
<b>Mounting Method</b>	19 mm dia. (¾”) thru-hole or mast-mount		
<b>Navigation accuracy GPS+GLO</b>	1.5m (50% CEP)		
<b>Environmental:</b>			
Operating Temp. -	-40C to +85C		
Storage Temp.	-45C to +85C		
Weatherproof	IP67		
Shock	Vertical axis 50G, other axis 30G 3 axis sweep - 15 min		
Vibration	10-200 Hz log sweep 3G		
Emissions	EN 55022		
Immunity	EN 61000-4-3, EN 61000-4-4, EN 61000-4-6		

## Ordering Information

33-5340-x-yy GPS/GLONASS /QZSS Smart Antenna  
33-5341-x-yy Non-magnetic, GPS/GLONASS/ Smart Antenna

27-0045-1 DB9 Test adaptor (For CMOS versions a CMOS/RS232 converter will also be required)

Where x= interface/voltage (0= RS232 12V; 1 = RS232 5V; 2 = CMOS 5V, 3 = CMOS, 3.3V, 5 = RS232 3.3V, 6 RS232 = 12V to 36V),  
yy= Radome (00= grey conical, 10=grey low profile, 01=white conical, 11=white low profile)

\* Contact Tallysman for pre-configuration in Pass-To-Pass Mode

## Tallysman Wireless Inc

36 Steacie Drive  
Ottawa ON, K2K 2A9 Canada  
Tel 613 591 3131 Fax 613 591 3121 [sales@tallysman.com](mailto:sales@tallysman.com)

The information provided herein is intended as a guide only and is subject to change without notice. This document is not to be regarded as a guarantee of performance. Tallysman Wireless Inc. hereby disclaims any or all warranties and liabilities of any kind. © 2014 Tallysman Wireless Inc. All rights reserved.

Rev-3.0